

SH(HD/SD-SDI) to HDMI Video and Audio Converter



BAT-SH

Features

- Auto Detection SDI Mode - HD/SD
- Re-clocked Loop-through HD/SD-SDI Output [BNC 75ohm]
- HDMI v1.3 Compliant
- Link Indicator LED (Green) : LED ON if SDI LOCK detected - SD(1 blink), HD(2 blink)
LED BLINK per one second if SDI is locked and HDMI not connected
- Video or Audio Error Indicator LED (Red) : LED ON if data error or SDI cable not connected
- Supports 8 audio channels (4 stereo pairs) - 48kHz sample rate
- Additional Analog Stereo Audio Output (Left RCA : White, Right RCA : Red)
- Selectable Luminance Range(0~255/16~235) by DIP Switch
- Selectable HD/SD Color Space Conversion by DIP Switch
- Power Cable Supplied
- 3 years warranty
- Camera-mounting bracket (option)

Specifications

- Input Video Format
720(1440) x 480i @ 59.94/60, 720(1440) x 576i @ 50
1280 x 720p @ 50, 1280 x 720p @ 59.94/60
1920 x 1080i @ 50, 1920 x 1080i @ 59.94/60
1920 x 1080p @ 23.94/24, 1920 x 1080p @ 25, 1920 x 1080p @ 29.97/30
1920 x 1080p @ 50, 1920 x 1080p @ 59.94/60
- Video Input
HD and SD-SDI (auto-selected), SMPTE-259/274/292/296/372/424/425,
1x BNC input, 1x BNC Loop-through output
- Video Output
HDMI v1.3a, 24/30/36 bits per pixel, RGB, 2.25Gbs, SD, HD, 1080p50/60
HDMI Standard Type A connector
- Audio Outputs:
HDMI embedded audio, 24 bit, 2 or 8 channels RCA-style analog outputs at -10dBV
- Input Power Range: +7V ~ +15V
- Power Consumption: 3Watt [Max]
- Power Adapter: +12V DC, 1.0A

Reuter Videosupport Digital
Alleestr.42
D-56410 Montabaur
Tel. +49 2602 9995477

Einführungspreis bis 31.07.2010: 399,- Euro netto EXW

reuter
Videosupport Digital